



Air Ionizing Cartridge

MODEL 6110/6110A

Simco-lon's self-contained compressed Air Ionizing Cartridge controls static charge in production, packaging, laboratory and other environments where static build-up can cause contamination, ESD, material handling problems or microprocessor lock-up. Compact and rugged, the cartridge can be used either for in-line ionization or as an ionizing blow-off gun. For in-line use, connect the 6110 to a compressed air source and it is ready to ionize any type of production equipment.


Model 6110A has an internal sensor initiates ionization only when the cartridge is triggered, ensuring ondemand control of static charge. Attached the 6110A to an ordinary air gun and the airstream is ionized for effective particle removal.

Features

- IsoStat® Technology
- · Shielded emitter points
- Compact size
- Internal airflow sensor (Model 6110A)
- · Optional blow-off gun kit

Benefits

- · Intrinsically balanced; no calibration needed
- · No shock hazard
- Adapts to compressed air lines
- On-demand ionization during gun operation
- · Fits any air gun



Model 6110/6110A **Input Voltage** 24 VAC, <1W from a wall transformer Discharge¹ <4 sec @ 6" (15.2 cm); ±1,000 to 100V Balance <±25V @ 6" (15.2 cm) **Ion Emission** IsoStat Technology **Emitter** Tungsten **LED Indicator** Green POWER Flow: At least 2 scfm Air Supply Connection: 1/4" NPT female (input and output); 1/8" NPT adapter available Model 6110A: Internal Airflow Sensor turns the ionizer off automatically when air is **Airflow Sensor** not flowing Model 6110: For continuous flow applications (without Airflow Sensor) Dimension 2.4" x 2.125" L (6.10 x 5.40 cm) not including fittings Weight 0.375 lb (0.17 kg) Warranty 2 year limited warranty Certification Wall Transformer 33-1420-01 **Input Voltage** 120 VAC ±10%, 50 Hz **Output Voltage** 24 VAC ±5% @ 500 mA Dimension 3.2"L x 2.2"W x 1.9"H (8.15 x 5.65 x 4.85 cm) Weight 0.9 lb (0.45 kg) c(UL)us Certification Wall Transformer 33-1430-01 & 33-1433-01 Input Voltage 230 VAC ±10%, 60 Hz **Output Voltage** 24 VAC ±5% @ 500 mA 3.2"L x 2.2"W x 1.9"H (8.15 x 5.65 x 4.85 cm) Dimension Weight 0.9 lb (0.45 kg) Certification

1. Tested in accordance with ANSI/ESD STM3.1-2015.

Ordering Information

91-6110	Model 6110 Air Cartridge Ionizer
92-6110-US	Model 6110 Air Cartridge Ionizer & 120 VAC Wall Transformer Kit
91-6110A	Model 6110A Air Cartridge Ionizer with Airflow Sensor
92-6110A-US	Model 6110 Air Cartridge lonizer with Airflow Sensor & 120 VAC Wall Transformer Kit
91-6150	Optional Air Gun/Hose Kit
33-1420-01	Wall Transformer Kit, 120V/24 VAC 500 mA, interconnect cable with RJ-11 6P/4C plug, US
33-1430-01	Wall Transformer Kit, 230V/24 VAC 500 mA, interconnect cable with RJ-11 6P/4C plug, EU
33-1433-01	Wall Transformer Kit, 230V/24 VAC 500 mA, interconnect cable with RJ-11 6P/4C plug, UK

IsoStat Technology

Simco-lon's IsoStat Technology guarantees intrinsically balanced ionization and eliminates complicated feedback circuits. Ionizers incorporating this technology never need calibration and require very little maintenance. IsoStat is based on a law of physics, Conservation of Charge, which states that charge cannot be created or destroyed in an isolated system. By isolating the ionizer's emitter points from ground, IsoStat ensures equal numbers of positive and negative ions.


Applications

In-line Ionization: Reduces ESD damage and microprocessor lock-up in:

- IC packaging and marking
- · Surface-mount equipment
- · Device testing equipment

Ionizing Blow-Off Gun: Removes particles in:

- · Printed circuit board assembly
- · Medical device manufacturing
- · Film processing





Optional Gun/Hose Kit (P/N 91-6150).



DS-6110_V12 - 6/23 © 2023 Simco-lon All rights reserved.

Simco-Ion, Technology Group

1141 Harbor Bay Parkway, Suite 201 Alameda, CA 94502

Tel: +1 (800) 367-2452 (in USA) Tel: +1 (510) 217-0460

ioninfo@simco-ion.com www.simco-ion.com/technology